

Daily generator checks (before starting the engine):

- Running hours from the previous day have been logged
- Generator is clean
- Fuel tank is at least 50 per cent full
- Look for any fuel leaks
- Check fuel cap is screwed on
- Check engine oil level
- Check engine oil condition
- Look for any radiator leaks
- Check radiator coolant level
- If the generator charges batteries, check they are well connected, that the charger works and the battery water level
- Look for leaks underneath the generator
- Check the exhaust system is not obstructed
- Check that the auto-start works
- Check all tools and equipment (including first aid kit) are present and in good condition